

## DDR DIMM Module Combination

Install at least one DIMM module on the slots. Memory modules can be installed on the slots in any order. You can install either single- or double-sided modules to meet your own needs.

Memory modules can be installed in any combination as follows:

Slot	Memory Module	Total Memory
DIMM 1 (Bank 0 & 1)	S/D	64MB~1GB
DIMM 2 (Bank 2 & 3)	S/D	64MB~1GB
DIMM 3 (Bank 4 & 5)	S/D	64MB~1GB
Maximum System Memory Supported		64MB~3GB

**S: Single Side**

**D: Double Side**

## Memory Speed/CPU Clock Support Matrix

Memory CPU Clock	DDR200	DDR266	DDR333	DDR400
100MHz			X	X
133MHz	X			
166MHz	X			
200MHz	X			Note 1

: Yes.

Note 1: 6 banks support. Please refer to [www.msi.com.tw](http://www.msi.com.tw) KT6 Delta page for the latest qualified memory list to ensure the system stability.

X: Not available .