



# Richland Bios Update Procedure

FAEIII  
Jacky Chen

Step 1. Use Trinity CPU series and boot to DOS mode

Trinity CPU model is shown as below: :

A4-5300B
A6-5400B
750K
740
730
A4-5300
A6-5400K
A8-5500
A8-5600K
A10-5700
A10-5800K

Step 2. Below table shows the MB model and the corresponding bios use.

主板型號	BIOS 版本	Package tool
FM2-A85XA-G65	E7793AMS.200	E7793V20.EXE
FM2-A75IA-E53	E7792AMS.200	E7792V20.EXE
FM2-A75MA-E35	E7721AMS.200	E7721V20.EXE
FM2-A55M-E35		
FM2-A85XMA-E35		
FM2-A55M-E33	E7721AMS.B10	E7721VB1.EXE
FM2-A55M-E23		
FM2-A55M-P33		
FM2-A75MA-P33		
FM2-A85XMA-P33		

Step 3. Extract package to root folder of bootable USB pen drive

Step 4 .Boot to DOS mode using bootable USB storage drive ◦

Step 5. Use the below command to flash the bios in DOS mode:

```
C:\>e7793v20.exe
```

Step 6. Press “Y” to continue updating BIOS

```
Do you want to update your BIOS ?  
Press (Y) to continue updating BIOS.  
Press (N) to cancel.  
Please don't remove USB drive or shutdown system during BIOS update process.
```

Step 7. Press any key and the system will auto reset

```
remove temporary files....ok  
BIOS update successfully!  
Press any key to continue...
```

Step 8. Change to Richland CPU after you shutdown the system.



Thank You Very Much  
for Your Attention

